



**45716/45717 (ZW3007)
Toggle Style
In-wall Dimmer (600W), No Neutral**

**45716 – White
45717 – Light Almond**



Key Features

- Turn ON/OFF and control the brightness level of the connected lighting manually or via Z-Wave remote control.
- May be used in single pole installation or with up to three 45741(WH) or 45761(LA) (both ZW2003) auxiliary switches in 2-way, 3-way or 4-way wiring configuration
- Blue LED indicates switch location in a dark room
- Can be Included in multiple Groups and Scenes
- Supports Advanced Configuration; Dim rates, Invert switch (if unit is installed upside down)
- Screw Terminal installation; requires wiring connections for Line (Hot), Load and Ground. Traveler wire required for multi pole installation. No Neutral.
- For use with Incandescent loads only; not intended for use with CFL or LED bulbs
- Use a standard-size wall plate for single gang installations (wall plate not included); Multi-gang box option available (removable 'side wings')
- LED can be enabled/disabled manually
- Inline traveler circuit protection
- White box contractor packaging
- UL Listed

SPECIFICATIONS

Power: 120 VAC, 60 Hz.

Signal (Frequency): 908.42 MHz.

Minimum Load: 40W

Maximum Load: 600W, Incandescent

Range: Up to 100 feet line of sight between the Wireless Controller and the closest Z-Wave receiver module.

Operating Temperature Range: 32-104° F (0-40° C)

For indoor use only. Not for use with appliance or motors

cUL Listed

Complies with FCC and Industry Canada regulations

JASCO Products

10 E. Memorial Rd

Oklahoma City, OK 73114

www.jascopeproducts.com

www.easyzwave.com

Z-Wave is a registered US trademark of Sigma Designs